

Lighting Consoles

- 16 Channels
- 8 Scenes
- 4 Chases
- Rugged

FC-816
Foot Controlled Console



SPECIFICATIONS

Channels:	16	Scenes:	8 Programmable
Chase:	4 Programmable 14 Steps each	Control Protocol:	LMX-128 (3 pin multiplex)
MIDI Functions:	Scene Select, Blackout, Chase Select, Chase Off, Chase Rate, Fade Rate	Circuitry:	Microprocessor Controlled, Non Volatile Memory
Power Consumption:	70ma Maximum	Audio Sync:	Line Input Jack
Power Input:	Phantom Powered from Dimmer	Size:	8.75"L x 5.5"W x 2"D
		Weight :	2.9 Pounds

Architect & Engineer's Specifications

The lighting control console shall have one manual 16 channel scene plus 8 preset programmable scenes. Scenes are activated by heavy duty switches. Four 14 step chases are user programmable. There shall be an overall master blackout control, control of the chase rate via tap control or an audio input jack, and fade control between chase steps. The console shall have a nonvolatile memory to retain scenes and chases when powered off.

The console is supplied standard with LMX-128 multiplex control on a 3 wire cable. The console is phantom powered via AS Series dimmers and draws 70ma maximum. Construction is of 16 gauge steel and no rivets are used in the construction. The console is 8.75"L x 5.5"W x 2"D and the weight is 2.9 pounds.

The lighting control console shall be a Lightronics FC-816.

5 YEAR WARRANTY

The 5 year warranty is valid if the Warranty Registration card is returned to Lightronics, Inc. within 30 DAYS of the purchase date.