

Architectural Systems

- 4 Scene Fader Station
- Screwless Faceplate Option
- Available in Ivory or White
- Fader Scene Control
- Status LEDs
- Blackout
- RS-485
- Double Gang Box
- Low Voltage

AF-2004 Remote Station



SPECIFICATIONS

Scenes:	4	Power Input:	18VDC provided by AR-1202RTC
Communication Bus:	Bidirectional RS-485	Size:	3.75"W x 4"H x 2.5"D
Wiring:	Dual Twisted Pair Data Cable	Weight:	0.48 Pounds

Architect & Engineer's Specifications

The AF-2004 is a wall mounted, four scene, digital remote for use with the Lightronics AR-1202RTC architectural dimmer and SR-528 scene saver. The AF-2004 provides full manual control of 4 scenes which have been prestored in the dimmer unit. It is fully digital and runs at high speed to provide no lag operation. "ALL FULL UP" and "ALL OFF" controls are provided. Lighted indicators clearly show which mode is active. AF-2004 wiring is low voltage. The AF-2004 connects to the AR-1202RTC via a shielded 4 conductor cable arranged as 2 twisted pairs. One pair connects to the data signals. The other pair carries the common and power. Scenes activated by the AF-2004 are created and stored in the AR-1202RTC. No setup or turn on procedure is needed. When the AR-1202RTC dimmer is powered on, the AF-2004 will also be powered. Communication with the AF-2004 is automatically established. The unit fits into a standard double gang wall switch box.

Power Input: 18VDC provided by AR-1202RTC; Dimensions: 3.75"W x 4"H x 2.5"D, Weight: 0.48 Pounds.

The unit shall be the Lightronics AF-2004.

5 YEAR WARRANTY

The 5 year warranty is valid if the Warranty Registration card is returned to Lightronics, Inc. within 30 DAYS of the purchase date.

