

Unity Architectural Systems

- 5 Scenes Push Button Station
- Screwless Faceplate
- Available in White
- Toggle Scene Control
- Status LEDs
- RS-485
- Single Gang Box
- Low Voltage

AK1005
Remote Station



SPECIFICATIONS

Scenes:	5	Power Input:	18VDC provided by AR1202
Communication Bus:	Bidirectional RS-485	Size:	2"W x 4"H x 1.5"D
Wiring:	Dual Twisted Pair Data Cable	Weight:	0.25 Pounds

Architect & Engineer's Specifications

The AK1005 is a 5 scene digital wall remote for use with the AR1202 architectural dimmer. All AK1005 wiring is low voltage. LED indicators in the scene buttons always show the currently active scene. The AK1005 connects to the AR1202 via a 4 conductor cable arranged as 2 twisted pairs. One pair carries the data signal. The other pair provides a common and power. Scenes activated by the AK1005 are created and stored in the AR1202 dimmer. No set up or turn on procedure is needed. When the AR1202 dimmer is powered, the AK1005 will also begin operating. The unit fits in a standard single gang wall switch electrical box.

Power Input: 18VDC provided by AR1202; Dimensions: 2"W x 4"H x 1.5"D, Weight: 0.25 Pounds.

The unit shall be the Lightronics AK1005.

5 YEAR WARRANTY

The 5 year warranty is valid if the Warranty Registration card is returned to Lightronics, Inc. within 30 DAYS of the purchase date.

