

<b>Rack Mounts</b>	RA-122	RA-121	RD-122	RD-121	RD-82	RE-82	RE-121
Channels	12	12	12	12	8	8	12
Watts/Channel	2400	1200	2400	1200	2400	2400	1200
Total Wattage	28800	14400	28800	14400	19200	19200	14400
Control Protocol	DMX-512 / Remote Stations	DMX-512 / Remote Stations	DMX and LMX	DMX and LMX	DMX and LMX	DMX or LMX	DMX or LMX
Built-In Chaser	-	-	8 Chases	8 Chases	8 Chases	-	-
Dimmer / Non-Dim Control	Yes						
Soft Start	Yes						
Softpatch	Yes	Yes	Yes	Yes	Yes	-	-
Set Levels Locally	Yes	Yes	Yes	Yes	Yes	ON / OFF Only	ON / OFF Only
Local Scene	99 Scenes	99 Scenes	1	1	1	-	-
Power Input	120/208VAC Three Phase, 80A each Leg OR 120/240VAC Single Phase, 120A each Leg	120/208VAC Three Phase, 40A each Leg OR 120/240VAC Single Phase, 60A each Leg	120/240VAC, 120A/Phase, 50/60 Hz Two Phase	120/240VAC, 60A/Phase, 50/60 Hz Two Phase	120/240VAC, 80A/Phase, 50/60 Hz Two Phase	120/240VAC, 80A/Phase, 50/60 Hz Two Phase	120/240VAC, 60A/Phase, 50/60 Hz Two Phase
Input Connections	Terminal Block						
Output Connections	Duplex or Terminal Strip Opt. Patchbay or Socapex	Duplex or Terminal Strip Opt. Patchbay or Socapex	Duplex or Terminal Strip Opt. Socapex	Duplex or Terminal Strip Opt. Stagepin, Patchbay or Socapex			
Overload Protection	20A Magnetic Circuit Breakers	10A Magnetic Circuit Breakers	20A Magnetic Circuit Breakers	10A Magnetic Circuit Breakers	20A Magnetic Circuit Breakers	20A Magnetic Circuit Breakers	10A Fuses
Filter Rise Time	600 uSec	350 uSec	350 uSec	350 uSec	350 uSec	350 uSec	350 uSec
UL508 Compliant	Yes	No	No	Yes	Yes	yes	yes
Weight (boxed)	50 pounds	29 pounds	50 pounds	31 pounds	32 pounds	32 pounds	29 pounds